
24Volt, 65Watt / MDS-065APS24 B



065APS24 B

Highlights & Features

- Safety Approvals to IEC 60601-1 3.1rd ed. & IEC 62368-1
- Compliant with IEC 60601-1-2 4th Ed. Requirements
- Low touch current (<0.1mA Normal & <0.3mA single fault)
- Over-Voltage/Load/Temperature & Short Circuit protections
- 2.5 Million Hours MTBF
- 2 x MOPP (means of patient protection)
- 3 years warranty

Safety Standards





CB Certified for worldwide use

Model Number: Unit Weight: Dimensions (W x L x H): 50.8x101.6x30.0 mm

MDS-065APS24 B 130 grams (4.6 Ounces) 2.0x4.0x1.2 in

General Description

The MDS series of embedded power supply come with universal AC input at 90Vac to 264Vac. Other features include low touch current, risk management report available and the electric shock protection comply with 2 x MOPP. The MDS series is certified for EMC standards according to EN 55011 for industrial, scientific and medical (ISM) radio-frequency equipment and EN 55032 for Information Technology Equipment (ITE) radio-frequency equipment. In addition, only recognized Japanese capacitors are used.

The MDS series of embedded power supply come with both medical and ITE safety approvals including UL/cUL/CQC/CE and CB certification and are fully compliant with RoHS Directive for environmental protection.

Model Information

Medical AC-DC Open Frame

Model Number	Input Voltage Range	Output Voltage	Output Current
MDS-065APS24 B	90-264Vac	24Vdc	2.71A

Model Numbering

MDS

Delta Medical Power Supply 065

Max wattage in the product series. Maybe lower at some voltage. $065 \rightarrow 65W$

Family Code

APS

24

Output Voltage Single Output: 24 for 24V

R



24Volt, 65Watt / MDS-065APS24 B

Specifications

Input Ratings / Characteristics

Nominal Input Voltago	100-240Vac
Nominal Input Voltage	100-240 VaC
Input Voltage Range	90-264Vac
Nominal Input Frequency	50-60Hz
Input Frequency Range	47-63Hz
Input Current (max)	1.5A @ 100Vac, 0.75A @ 240Vac
Efficiency (typ.)	88.4%, Reference Fig.1
Standby Power (max)	0.3W
Inrush Current (typ.)	40A @ 115Vac, 80A @ 230Vac
Touch Current (max)	0.1mA @ 264Vac NC1), 0.3mA @ 264Vac SFC2)

¹⁾ NC: normal condition 2) SFC: single fault condition




Fig.1 Efficiency versus output load

Output Ratings / Characteristics

Nominal Output Voltage	24Vdc
Total regulation	± 1.5%
Output Current	2.71A
Output Power	65W
Output Peak Load	3.79A*
Line Regulation (max)	±0.5%
Load Regulation (max)	±1%
Ripple & Noise (typ.)	32.8mV pk-pk @ Full load, Reference Fig. 2,
Start-up Time(max)	3000ms @ 115Vac
Hold-up Time(typ.)	15ms @ 115Vac
	20ms @ 100Vac with 45W
Dynamic Response (Overshoot & Undershoot O/P Voltage)	± 5% @ 50-100% load

^{*}Output peak can last 8 sec with 10% duty cycle, and the output voltage should meet ±5% voltage regulation at normal input voltage



24Volt, 65Watt / MDS-065APS24 B





Fig. 2 Ripple & Noise example, 20MHz BW

Ripple & Noise measurement circuit



Mechanical

Dimensions (W x L x H)		50.8 x 101.6 x 30.0 mm(2 x 4 x 1.2 in)
Weight (typ.)		130 grams (4.6 Ounces)
Terminal	Input	JST 2P
	Output	JST 4P

Environment

Common dia a Air Tomas and an	Operating	-10°C to +70°C	
Surrounding Air Temperature	Storage	-40°C to +85°C	
Power De-rating		-10°C to +50°C 100% load	
		50°C to 70°C de-rate power by 2.5% / °C, See Fig. 3	
Operating Humidity		5-95% RH (Non-Condensing)	
Storage Humidity		5-95% RH (Non-Condensing)	
Operating Altitude		Up to 3,000 meters (up to 9,842 feet or 106-70kPa)	
Shock Test (Non-Operating)		50G, 11ms, 3 shocks for each direction	
Vibration (Non-Operating)		5-500Hz, 2.09Grms, 20 minute for each three axis	



24Volt, 65Watt / MDS-065APS24 B

Protections

Over Voltage (max)	150%, Latch Mode
Over Load / Over Current	150%~210% of rated load current, Hiccup Mode (Non-Latching, Auto-Recovery)
Over Temperature	Hiccup Mode,
•	(Non-Latching, Auto-Recovery)
Ob ant Oireanit	Hiccup Mode,
Short Circuit	(Non-Latching, Auto-Recovery)
Protection Against Shock	Class I with PE* connection

^{*}PE: Protective Earth

Reliability Data

MTBF (typ.)	2.5 Million Hours based on Telecordia SR-332
-------------	--

Safety Standards / Directives

Medical Safety ITE Safety		IEC60601-1: (Ed.3,2005), EN60601-1:2006, CAN/CSA-C22.2 No. 60601-1:08, ANSI/AAMI ES60601-1: (Ed.3,2005) IEC 60601-1 Edition 3.1 (2012), EN60601-1 (2006) + A11 + A1 + A12, CAN/CSA-C22.2 NO. 60601-1:14, ANSI/AAMI ES60601-1:2005/(R)2012 IEC60950-1 (Ed.2,2005), IEC62368-1, GB4943.1-2011 GB9254-2008, GB17625.1-2003	
Galvanic Isolation	Input to Output	4000 Vac	
	Input to Ground	1500 Vac	
	Output to Ground	500 Vac	



24Volt, 65Watt / MDS-065APS24 B

EMC (Compliant with IEC 60601-1-2 4th Ed. Requirements)

EMC / Emissions		EN55011/EN55032,FCC Title 47:Class B
Harmonic Current Emissions	IEC61000-3-2	Meet Class A limit
Immunity to		
Voltage Flicker	IEC61000-3-3	
Electrostatic Discharge	IEC61000-4-2	Level 4 Criteria A ¹⁾ Air Discharge: 15kV Contact Discharge: 8kV
Radiated Field	IEC61000-4-3	Criteria A ¹⁾ 80MHz-2700MHz, 10V/m AM modulation 385MHz-5785MHz, 28V/m Pulse mode and other modulation
Electrical Fast Transient / Burst	IEC61000-4-4	Level 3 Criteria A ¹⁾ :2kV
Surge	IEC61000-4-5	Level 3 Criteria A ¹⁾ Common Mode ³⁾ : 2kV Differential Mode ⁴⁾ : 1kV
Conducted	IEC61000-4-6	Level 2 Criteria A ¹⁾ 150kHz-80MHz, 3Vrms, 6Vrms at ISM bands and Amateur radio bands
Power Frequency Magnetic Fields	IEC61000-4-8	Criteria A ¹⁾ Magnetic field strength 30A/m
Voltage Dips	IEC61000-4-11	Criteria A ¹⁾ 0% U _T , 0.5 cycle (10ms) , 0°/45°/90°/135°/180°/225°/270°/315°/360°
		Criteria B ²⁾ 0% U _T , 1 cycle (20ms), 0°
		Criteria A ¹⁾ 70% U _T , 25 cycle (500ms), 0°
		Criteria B ²⁾ 0% U _T , 250 cycle (5000ms), 0°

¹⁾ Criteria A: Normal performance within the specification limits




²⁾ Criteria B: Output out of regulation, or shuts down during test. Automatically restore to normal operation after test.

³⁾ Asymmetrical: Common mode (Line to earth)
4) Symmetrical: Differential mode (Line to line)

24Volt, 65Watt / MDS-065APS24 B

Block Diagram






24Volt, 65Watt / MDS-065APS24 B

Dimensions

W x L x H: 50.8 x 101.6 x 30 mm (2.0 x 4.0 x 1.2 in)



TAB.1 COMPONENT TABLE

ITEM	PART NAME	COLOR
1	AC INPUT (CN1) JST: B2P3-VH(LF)(SN) MATING WITH JST: VHR-3N	WHITE
2	DC OUTPUT (CN2) JST: B4P-VH(LF)(SN) MATING WITH JST: VHR-4N	WHITE
3	PCB	
4	SPEC LABEL	WHITE

Notes

- Dimensions are in mm (in).
- For optimum EMC performance, the two mounting points with ground symbol shown in mechanical drawing need to be connected together to system earth case.
- Method of protective earth connection:
 - When system (End products') protective earth connection is connected to system's (or end products)' enclosure/cover (afterward named "system" for short).
 - Two mounting holes which are marked ground symbols in mechanical drawing are needed to link system together by conductive screw.



24Volt, 65Watt / MDS-065APS24 B

Power De-rating




Fig. 3

Functions

Start-up Time

The time required for the output voltage (Vo) to reach 90% of its set value, after the input AC voltage is applied.


Rise Time

The time required for the output voltage (Vo) to change from 10% to 90% of its steady state value.

Hold-up Time

Hold up time is the time when the AC input collapses and output voltage retains regulation for a certain period of time. The time required for the output to reach 95% of its set value, after the input voltage is removed.

■ Graph illustrating the Start-up Time, Rise Time, and Hold-up Time






24Volt, 65Watt / MDS-065APS24 B


Dynamic Response

The power supply output voltage will remain within ±5% of its steady state value, when subjected to a dynamic load change from 50 to 100% of its rated current.



Inrush Current

Inrush current is the input current that occurs when the input voltage is first applied. For AC input voltages, the maximum peak value of inrush current will occur during the first half cycle of the applied AC voltage. This peak value decreases exponentially during subsequent cycles of AC voltage.



Overvoltage Protection


The power supply's overvoltage circuit will be activated when its internal feedback circuit fails. The output voltage shall not exceed its specifications defined on Page 4 under "Protections". Power supply will latch off, and require removal/re-application of input AC voltage in order to restart.

Short Circuit Protection

The power supply's output OLP/OCP function also provides protection against short circuits. When a short circuit is applied, the output current will operate in "Hiccup mode", as shown in the illustration in the OLP/OCP section on this page. The power supply will return to normal operation after the short circuit is removed

Overload & Over current Protections

The power supply's Overload (OLP) and Over current (OCP) Protections will be activated when output current is between 150% and 210% of Io (Max load). Upon such an occurrence, Vo will start to drop. Once the power supply has reached its maximum power limit, the protection will be activated. and the power supply will go into "Hiccup mode" (Auto-Recovery). The power supply will recover once the fault condition causing the OLP and OCP is removed and Io is back within the specified limit.



Additionally, if the Io is <115% but >100% for a prolong period of time (depending on the load), the Over Temperature Protection (OTP) will be activated due to high temperature on critical components. The power supply will then go into hiccup mode until the fault is removed; and, the input voltage is removed, then reapplied.

Over Temperature Protection

As mentioned above, the power supply also has Over Temperature Protection (OTP). This is activated when the overload condition persists for an extended duration and the output current is below the overload trigger point but >100% load. In the event of a higher operating condition at 100% load, the power supply will run into OTP when the surrounding air temperature is higher than the operating temperature. When activated, the output voltage will go into hiccup mode until the input voltage is removed; then, reapplied, and the surrounding air temperature drops to its normal operating temperature.



24Volt, 65Watt / MDS-065APS24 B

Certificate



Delta has been certified as meeting the requirement of ISO 13485: 2003 and EN ISO 13485:2012 for the design and manufacture of switching power supply and adaptor for medical device.



In addition to a UL Total Certification Program (TCP) approved client laboratory for IEC62368-1. Delta also has participated UL Client Test Data Program (CDTP) for IEC 60601

Attention

Delta provides all information in the datasheets on an "AS IS" basis and does not offer any kind of warranty through the information for using the product. In the event of any discrepancy between the information in the catalog and datasheets, the datasheets shall prevail (please refer to www.DeltaPSU.com for the latest datasheets information). Delta shall have no liability of indemnification for any claim or action arising from any error for the provided information in the datasheets. Customer shall take its responsibility for evaluation of using the product before placing an order with Delta.

Delta reserves the right to make changes to the information described in the datasheets without notice.



24Volt, 65Watt / MDS-065APS24 B

Document Revision Record

Date	Item	Content Revised	Page Affected	Rev
2019/1/9	1	Modify from Rev.06 (2018.06.08)	All	07
	2	Change "Operating Humidity "Description to 5-95% RH (Non-Condensing)	3	
	3	Delete Environment "Non-Operating Altitude "Description	3	
	4	Update EMC/Emission from EN55022 to EN55032	5	
	5	Update PD drawing	7	
	6	Add "Attention"	10	
2020/09/03	1	- Update 62368 - Remove RoHS	1,4,10 1,4,10	08

